

Faster network disruption from layered oscillatory dynamics

Cite as: Chaos 32, 121102 (2022); <https://doi.org/10.1063/5.0129123>

Submitted: 03 October 2022 • Accepted: 14 November 2022 • Published Online: 05 December 2022

 Melvyn Tyloo



View Online



Export Citation



CrossMark



Chaos

Special Topic: Nonlinear Model
Reduction From Equations and Data

Submit Today!

Faster network disruption from layered oscillatory dynamics

Cite as: Chaos 32, 121102 (2022); doi: 10.1063/5.0129123

Submitted: 3 October 2022 · Accepted: 14 November 2022 ·

Published Online: 5 December 2022



View Online



Export Citation



CrossMark

Melvyn Tyloo^{a)} 

AFFILIATIONS

Theoretical Division, Los Alamos National Laboratory, Los Alamos, New Mexico 87545, USA and Center for Nonlinear Studies (CNLS), Los Alamos National Laboratory, Los Alamos, New Mexico 87545, USA

Note: This paper is part of the Focus Issue on Disruption of Networks and System Dynamics.

^{a)}Author to whom correspondence should be addressed: mtyloo@lanl.gov

ABSTRACT

Nonlinear complex network-coupled systems typically have multiple stable equilibrium states. Following perturbations or due to ambient noise, the system is pushed away from its initial equilibrium, and, depending on the direction and the amplitude of the excursion, it might undergo a transition to another equilibrium. It was recently demonstrated [M. Tyloo, J. Phys. Complex. 3 03LT01 (2022)] that layered complex networks may exhibit amplified fluctuations. Here, I investigate how noise with system-specific correlations impacts the first escape time of nonlinearly coupled oscillators. Interestingly, I show that, not only the strong amplification of the fluctuations is a threat to the good functioning of the network but also the spatial and temporal correlations of the noise along the lowest-lying eigenmodes of the Laplacian matrix. I analyze first escape times on synthetic networks and compare noise originating from layered dynamics to uncorrelated noise.

Published under an exclusive license by AIP Publishing. <https://doi.org/10.1063/5.0129123>

Complex networked systems are often made of different layers of dynamics that somehow interact together. Due to this intricate structure, noise or perturbations affecting one layer are typically transferred to other layers with additional statistical properties, e.g., spatial and temporal correlations. The latter might have serious consequences on the desired functioning of some layers, one of them being the amplification of fluctuations.¹ Together with the inherent multistability of nonlinearly coupled dynamical systems, noise acting on one layer may be more prompt to drive other layers outside their initial basin of attraction, through a transition to another equilibrium, if such a state exists. Here, I investigate how first escape times are affected by noise propagating through a layered system and compare it to uncorrelated noise.

I. INTRODUCTION

Various systems in nature and engineered applications can be modeled as individual dynamical units, interacting with one another in a complex way such as neurons spiking together in the brain² or rotating masses of power generators evolving at the same frequency in large-scale transmission networks.³ Collective phenomena taking

place in these systems such as synchronization are enabled by both the internal dynamics and the interaction within the individual units.⁴ Another remarkable feature of such systems is multistability. Thanks to nonlinearities in the interaction, numerous equilibria might exist, each of them having their own basin of attraction.^{5,6} Due to external perturbations such as environmental noise or faults occurring at some components, the whole system might undergo transitions between equilibrium points. In many instances, this is not desirable as both the transient dynamics and the new equilibrium might threaten the correct operation of the system or even cause damages.⁷ An important task is to predict such a transition as they could disrupt the desired functioning state of the networked system. The latter question has been investigated mostly in coupled systems made of a single layer of interaction, usually subjected to spatially uncorrelated noise.⁸⁻¹¹ However, many applications require more involved coupling structures in order to correctly describe them.¹² A natural extension of the single layer framework is to include multiple layers of dynamical systems.^{13,14} In such layered dynamics, noise acting on one sub-network propagates to other layers with system-specific correlations.¹ In other words, when going through a layer, the noise acquires some specific statistical properties, which is then injected into other layers. Including such a system-specific correlation in the noise might increase the level of

fluctuations and, thus, the risk of transitions between equilibria. This is depicted in Fig. 1, where uncorrelated noise is acting on the first layer [blue in panel (a)], which is then transmitted to the second one [red in panel (a)]. In this setting, the second layer is subjected to correlated noise, which we describe below. Both layers are made of a single cycle network, which has multiple equilibria as illustrated in Fig. 1(b). Due to the noise injected in both of them, the two layers are pushed away from their initial equilibrium and, depending on the noise amplitude and direction, eventually leave their initial basin of attraction. Transitions between basins of attraction can be detected by changes in the winding numbers in each layer q_1 and q_2 [see Fig. 1(c)]. One clearly sees that, while the first layer does not operate any transition, the second one exits its initial basin of attraction multiple times. Similar transitions were observed for a single layer system^{8,10} and related to the eigenvalues of the network Laplacian matrix and the distance between the initial fixed point and the closest saddle point with a single unstable direction.¹¹ Here, I consider layered systems where each layer has its own individual units, nonlinearly coupled on a complex network. The different layers interact together via a coupling function. It was recently shown that noise acting on a layer might be strongly amplified in the other layers depending on the network connectivities.¹ In addition to being

amplified, the noise structure seems to align with the lowest-lying eigenmodes of the network Laplacian. Building on these results, I investigate the first escape time from the initial basin of attraction in one layer due to noise originating from connected layers. Remarkably, correlations in space and time of this type of noise seem more efficient in driving the system through a transition to another basin than uncorrelated noise.

This paper is organized as follows. In Sec. II, I introduce the two-layer system of nonlinearly coupled oscillators considered, recall previous results,¹ and discuss escape from the basin of attraction. Numerical results are presented in Sec. III and conclusions in Sec. IV.

II. NOISY NONLINEAR LAYERED OSCILLATORS

A. Kuramoto dynamics and its linearization

In order to investigate the effect of noise in layered networks, I consider a simple two-layer system made of Kuramoto oscillators¹⁵ as the one shown in Fig. 1(a). Note that the results below may apply to a larger set of diffusively coupled systems. Their dynamics is governed by $2n$ coupled differential equations

$$\dot{x}_i = \omega_i^{(1)} - \sum_{j=1}^n b_{ij}^{(1)} \sin(x_i - x_j) + \eta_i, \quad i = 1, \dots, n, \tag{1}$$

$$\dot{y}_i = \omega_i^{(2)} - \sum_{j=1}^n b_{ij}^{(2)} \sin(y_i - y_j) + f_i(\{x_k\}, \{y_k\}), \quad i = 1, \dots, n,$$

where degrees of freedom and natural frequencies, respectively, in layers 1 and 2 are denoted as $\{x_k\}$, $\{y_k\}$ and $\omega_k^{(1)}$, $\omega_k^{(2)}$. The undirected coupling network in the l th layer is given by the adjacency matrix elements $b_{ij}^{(l)} \geq 0$, and f_i is a coupling function between the two layers. The noise acting on the first layer is encoded in η_i that is taken as white and uncorrelated in space, i.e., $\langle \eta_i(t) \eta_j(t') \rangle = \delta_{ij} \eta_0^2 \delta(t - t')$. This model made of Kuramoto oscillators is a nonlinear version of the one used in Ref. 1. Thanks to the sine coupling and provided that $b_{ij}^{(l)}$'s are sufficiently large compared to the distributions of $\omega_i^{(l)}$'s, Eq. (1) may have multiple stable or unstable fixed points $(\{x_k^{(0)}\}, \{y_k^{(0)}\})$, depending on the coupling networks. In both cases, they satisfy

$$0 = \omega_i^{(1)} - \sum_{j=1}^n b_{ij}^{(1)} \sin(x_i^{(0)} - x_j^{(0)}), \quad i = 1, \dots, n, \tag{2}$$

$$0 = \omega_i^{(2)} - \sum_{j=1}^n b_{ij}^{(2)} \sin(y_i^{(0)} - y_j^{(0)}) + f_i(\{x_k^{(0)}\}, \{y_k^{(0)}\}),$$

$$i = 1, \dots, n.$$

In the following, I consider a simple coupling function $f_i(\{x_k\}, \{y_k\}) = d(x_i - n^{-1} \sum_j x_j)$ where degrees of freedom in the first layer tune the natural frequencies in the second one, and d serves as a tuning parameter. The dynamics of small deviations close to a stable fixed point is given by the Taylor expansion of Eq. (1) to the first order in




FIG. 1. (a) Two-layer system with a single cycle in each layer. (b) Three different fixed points with $q = -1, 0, 1$ are illustrated for a $n = 5$ node system, where the orientation of the arrows represents the degrees of freedom. (c) Time-evolution of the winding numbers q_1 and q_2 in each layer (c) of the two-layer system shown in panel (a), corresponding to Eq. (1) with parameters such that injected noise amplitudes are the same in both layers. The two layers have the same cyclic coupling network of size $n = 40$ nodes. Transitions between different basins of attraction are tracked by observing changes in values of $q_{1,2}$. Noise amplitudes are the same in both layers; however, their spatial and temporal correlations are different.

$[\delta x_i(t), \delta y_i(t)] = [x_i(t) - x_i^{(0)}, y_i(t) - y_i^{(0)}]$, and read

$$\dot{\delta x}_i = - \sum_{j=1}^n b_{ij}^{(1)} \cos(x_i^{(0)} - x_j^{(0)}) (\delta x_i - \delta x_j) + \eta_i, \tag{3}$$

$$\dot{\delta y}_i = - \sum_{j=1}^n b_{ij}^{(2)} \cos(y_i^{(0)} - y_j^{(0)}) (\delta y_i - \delta y_j) + d \left(\delta x_i - n^{-1} \sum_j \delta x_j \right),$$

which are diffusive linear systems. Indeed, one can define the weighted Laplacian matrices,

$$\mathbb{L}_{ij}^{(1)}(\{x_i^{(0)}\}) = \begin{cases} -b_{ij}^{(1)} \cos(x_i^{(0)} - x_j^{(0)}), & i \neq j, \\ \sum_k b_{ik}^{(1)} \cos(x_i^{(0)} - x_k^{(0)}), & i = j, \end{cases}$$

$$\mathbb{L}_{ij}^{(2)}(\{y_i^{(0)}\}) = \begin{cases} -b_{ij}^{(2)} \cos(y_i^{(0)} - y_j^{(0)}), & i \neq j, \\ \sum_k b_{ik}^{(2)} \cos(y_i^{(0)} - y_k^{(0)}), & i = j, \end{cases}$$

which depend on both the initial coupling networks in each layer and the considered equilibrium. Using these Laplacian matrices, Eq. (3) is conveniently rewritten in a vector form as

$$\begin{aligned} \dot{\delta \mathbf{x}} &= -\mathbb{L}^{(1)}(\{x_i^{(0)}\}) \delta \mathbf{x} + \boldsymbol{\eta}, \\ \dot{\delta \mathbf{y}} &= -\mathbb{L}^{(2)}(\{y_i^{(0)}\}) \delta \mathbf{y} + d \overline{\delta \mathbf{x}}, \end{aligned} \tag{4}$$

where $\overline{\delta x}_i = \delta x_i - n^{-1} \sum_j \delta x_j$. From the Laplacian properties of $\mathbb{L}_{ij}^{(1)}(\{x_i^{(0)}\})$ and $\mathbb{L}_{ij}^{(2)}(\{y_i^{(0)}\})$, their eigenvalues satisfy: $0 = \lambda_1^{(k)} < \lambda_2^{(k)} < \dots < \lambda_n^{(k)}$ for $k = 1, 2$ with the first eigenvector being constant, i.e., $\mathbf{u}_1^{(k)} = (1, \dots, 1)/\sqrt{n}$ for $k = 1, 2$. The latter modes correspond to a symmetry of the system as any shift along it does not modify the dynamics or the fixed points. The second smallest eigenvalue $\lambda_2^{(k)}$ is usually called *algebraic connectivity* of the network, with its corresponding eigenvector $\mathbf{u}_2^{(k)}$ called *Fiedler mode*. The larger the algebraic connectivity, the better connected is the network, in the sense that even the slowest modes are quickly damped. The solution of Eq. (4) is obtained by expanding the deviations over the eigenvectors as $\delta x_i = \sum_{\alpha} c_{\alpha}^{(1)} u_{\alpha,i}^{(1)}$, $\delta y_i = \sum_{\alpha} c_{\alpha}^{(2)} u_{\alpha,i}^{(2)}$.

B. Amplification of the fluctuations

It has been shown recently that, for linear systems governed by the dynamics of Eq. (4), spatially uncorrelated and white in time noise acting on the first layer x_i 's might lead to amplified fluctuations in the second layer y_i 's.¹ Indeed, the variance of the degrees of freedom in the first layer is generated by η_i 's, which are i.i.d. and white in time, and yields¹ (see Appendix A for details)

$$\langle \delta x_i^2 \rangle = \frac{\eta_0^2}{2} \sum_{\alpha} \frac{u_{\alpha,i}^{(1)2}}{\lambda_{\alpha}^{(1)}}, \tag{5}$$

where $\langle \dots \rangle$ refers to the average. In contrast, the variance in the second layer is generated by the x_i 's, which play the role of additive noise that is both correlated in space and time as shown by their

two-point, time shifted correlator,¹

$$\langle \delta x_i(t) \delta x_j(t') \rangle = \frac{\eta_0^2}{2} \sum_{\alpha} \frac{u_{\alpha,i}^{(1)} u_{\alpha,j}^{(1)}}{\lambda_{\alpha}^{(1)}} e^{-\lambda_{\alpha}^{(1)} |t-t'|}. \tag{6}$$

Using the latter correlator together with Eq. (4) allows us to calculate the variance in the second layer, which yields

$$\begin{aligned} \langle \delta y_i^2 \rangle &= d^2 \frac{\eta_0^2}{2} \sum_{\alpha, \beta, \gamma} \sum_{k,l} \frac{u_{\gamma,k}^{(1)} u_{\gamma,l}^{(1)} u_{\alpha,k}^{(2)} u_{\beta,l}^{(2)} [2\lambda_{\gamma}^{(1)} + \lambda_{\alpha}^{(2)} + \lambda_{\beta}^{(2)}]}{\lambda_{\gamma}^{(1)} (\lambda_{\alpha}^{(2)} + \lambda_{\beta}^{(2)}) (\lambda_{\gamma}^{(1)} + \lambda_{\alpha}^{(2)}) (\lambda_{\gamma}^{(1)} + \lambda_{\beta}^{(2)})} \\ &\quad \times u_{\alpha,i}^{(2)} u_{\beta,i}^{(2)}. \end{aligned} \tag{7}$$

For linearly coupled oscillators, the variance is exactly described by Eqs. (5) and (7). Depending on the overlap between the slowest eigenvectors of $\mathbb{L}_{ij}^{(1)}(\{x_i^{(0)}\})$ and $\mathbb{L}_{ij}^{(2)}(\{y_i^{(0)}\})$, fluctuations in the second layer might be strongly amplified. In the particular case where the networks are the same in both layers, i.e., $\mathbb{L}_{ij}^{(1)}(\{x_i^{(0)}\}) = \mathbb{L}_{ij}^{(2)}(\{y_i^{(0)}\})$, Eq. (7) simplifies to

$$\langle \delta y_i^2 \rangle = d^2 \frac{\eta_0^2}{4} \sum_{\alpha} \frac{u_{\alpha,i}^2}{\lambda_{\alpha}^3}. \tag{8}$$

Due to the third power of λ_{α} at the denominator, the variance is dominated by the slowest modes. So, not only the overall amplitude of the fluctuations might be large but also their shape follows those of the slowest modes. This is shown in Fig. 2. For both x_i 's and y_i 's, an important contribution to the variance comes from $u_{2,i}^2$ [see Eqs. (5) and (8)]. However, for the second one, this contribution dominates even more due to the denominator in Eq. (8). One clearly sees that nodes corresponding to the largest $u_{2,i}^2$'s (lighter colors) have the largest standard deviations in the second layer. Therefore, the second layer is perturbed away from its initial equilibrium mostly along the directions of the slowest eigenmodes.

C. Escape from the basin of attraction

While the linear system on the first line of Eq. (4) has a single fixed point (neglecting the symmetry along $\mathbf{u}_1^{(1)}$), it is not the case of nonlinearly coupled systems, which may have multiple stable fixed points each of them with their own basin of attraction. If the excursion from the initial equilibrium becomes too important, the system undergoes a transition to another basin of attraction corresponding to another fixed point or reaches an unstable region of the phase space. Obviously, large perturbations leading to important excursions result in short first escape times. However, not only the amplitude but also the direction of the perturbation matter. Indeed, basins of attraction are not isotropic,^{5,16,17} and excursion along specific directions may lead to faster transitions. This is already pointed at by Fig. 1(c), where the amplitudes of the noise acting on layers 1 and 2 are the same. However, the second layer (in red) operates more transitions than the first one (in blue), which stays in its initial basin of attraction.

In order to detect escapes, one can use the winding number defined on a cycle c as

$$q = (2\pi)^{-1} \sum_{i \in c} |z_i - z_{i+1}|_{[-\pi, \pi)}, \tag{9}$$




FIG. 2. Time-evolution of x_i 's and y_i 's following Eq. (1) with $d = 1$ for the system made of two layers of $n = 20$ nodes depicted on the right. The colors represent the squared amplitude of the slowest eigenvector, i.e., $u_{2,i}^2$ (where I dropped the superscript as the networks are the same in both layers). Lighter colors correspond to larger values of $u_{2,i}^2$, which also have larger standard deviations in the second layer (y_i 's).

where $|\cdot|_{[-\pi,\pi)}$ brings the argument into the interval $[-\pi, \pi)$ and z_i is the degree of freedom of the i th oscillator in the cycle. The winding number is, therefore, an integer given by the number of times that the degrees of freedom wind around the origin along a cycle c [see Fig. 1(b)]. On a planar meshed network, one can further define a winding vector \mathbf{q} whose components are given by the winding number on each cycle composing the network. Each stable fixed point of Eq. (1) is unambiguously identified by a pair of winding vectors $(\mathbf{q}_1, \mathbf{q}_2)$, where \mathbf{q}_l is the collection of winding numbers on each cycle of the l th layer. Therefore, by recording $(\mathbf{q}_1, \mathbf{q}_2)$, one is able to detect basin's escapes independently in each layer. This technique is useful in cases where one is able to measure the flows on each edge and, therefore, determine the winding numbers on each cycle. Another way of measuring first escape times is simply by letting the system relax at every time step and checking that the stable fixed point is the same as the original. This is for sure more precise in determining the first escape time; however, it is much more costly in terms of numerical simulations.

III. NUMERICAL SIMULATIONS

In this section, I compare the first escape time in both layers varying the settings. I first consider a system made of two times the same network. To disentangle the effects of amplitude and shape of the noise coming from the first layer, I investigate the situations where (i) the noise is not rescaled, i.e., large fluctuation might appear in the second layer; (ii) rescaled noise in the second layer

so that noise amplitudes in both layers are the same on average, but their shapes are different. The latter is done by tuning the d parameter in the inter-layer coupling function. More details are given below. Then, I briefly consider the case of different networks. The method to detect escape based on winding numbers is used for cycle networks, and a combination of the more computationally expensive one and the winding numbers for more complex networks (see Sec. II C). For simplicity, I consider identical oscillators, i.e., $\omega_i^{(l)} = 0, \forall i, l$.

A. Same networks

When the two networks are the same, the noise injected in the second layer has statistical properties that are directly connected to its structure [see Eq. (6)]. One, therefore, expects an important difference in the first escape times of the two layers. More precisely, for networks with low algebraic connectivity, fluctuations are amplified in the second layer, and, therefore, one expects shorter first escape times for the second layer compared to the first one. For the network with high algebraic connectivity, one expects the opposite, as fluctuations are reduced in the second layer.

1. Amplification

Here, we set $d = 1$ in the coupling function, meaning that the noise in the second layer has both a specific modal structure and is




FIG. 3. First escape time T_{esc} as a function of the noise amplitude in the first layer η_0 with $d = 1$. This system is composed of two cycle networks of size $n = 40$ in each layer. Each cross gives the median over 40 realizations. The solid lines show the median first escape time for the first (blue) and second (red) layers. Shaded areas show the 0.25- and 0.75-quantiles.

potentially strongly amplified or reduced. In this case, the two networks are the same and, therefore, share the same eigenvectors and eigenvalues. One expects enhanced fluctuations in the second layer if the algebraic connectivity is less than one, i.e., $\lambda_2 \ll 1$.¹ This is, in particular, the case for large cycle networks whose algebraic connectivity scales with n as $\lambda_2 = 2 - 2 \cos(2\pi/n)$. Here, I focus on such networks with amplification, as those with $\lambda_2 \gg 1$ have reduced fluctuations in the second layer and, thus, are less likely to leave the initial basin of attraction. Figure 3 gives the first escape times for both layers in a system made of two cycles. One clearly sees that the first escape time is shorter by several orders of magnitudes in the second layer compared to the first one for noise amplitude $\eta_0 < 2.5$. Then, for larger η_0 , the first layer exits its initial basin of attraction faster than the second one. In this regime, the dynamics in the first layer is essentially dominated by the noise with only little influence coming from the coupling network. The noise injected in the second layer may, therefore, not have any amplification or specific structure in this case as the linearized calculation presented here does not apply anymore.

2. Rescaled noise

In order to differentiate the effect of noise amplitude and shape, one needs to rescale the noise coming from the first layer so that amplitudes are the same in both layers. The noise coming from the first layer and to which is subjected the second layer is given by $\xi = d \delta \mathbf{x}$. The noise variance in the first layer is η_0^2 . Choosing $d^2 = 2 / \sum_{\alpha} \lambda_{\alpha}^{(1)-1}$ produces an input noise in the second layer that has on average a variance of η_0^2 , i.e.,

$$n^{-1} \sum_i \langle \xi_i^2 \rangle = \eta_0^2, \tag{10}$$




FIG. 4. First escape time T_{esc} as a function of the noise amplitude in the first layer η_0 with $d = \left(2 / \sum_{\alpha} \lambda_{\alpha}^{(1)-1}\right)^{1/2}$. This system is composed of two cycle networks of size $n = 40$ in each layer. Each cross gives the median over 40 realizations. The solid lines show the median first escape time for the first (blue) and second (red) layer. Shaded areas show the 0.25- and 0.75-quantiles.

so that both layers are subjected to noises of similar variance on average but yet have different shapes and time correlations [see Eq. (6)]. This is illustrated in Fig. 4 for a system made of two cycles, where the noise in the second layer is rescaled. Interestingly, one observes that the first escape time in the second layer is still shorter than in the first one for $\eta_0 < 1.7$. This means that the structure of noise as discussed in Sec. II B favors faster escapes from the initial basin of attraction compared to uncorrelated noise.

B. Different networks

For two different networks, noise transmission essentially depends on the overlap between $u_{\alpha,l}^{(1)}$ and $u_{\beta,l}^{(2)}$ for the slowest modes. If the overlap is low, one expects that the noise is transmitted mostly without amplification and, therefore, the first escape times should be similar in both layers. In the other situation where the overlap is significant, one expects different first escape times in the two layers.

1. Amplification

Similar effects as in Sec. III A 1 can be observed when networks are different in the two layers. Here, I consider two networks generated following Watts–Strogatz¹⁸ procedure with first and second nearest neighbor couplings and low rewiring probabilities. Doing so, the algebraic connectivities of both networks are smaller than one, i.e., $\lambda_2^{(1)} = 0.033$ $\lambda_2^{(2)} = 0.084$, and the overlap between their slowest eigenvectors is sufficiently different from zero, i.e., $\sum_i u_{2,i}^{(1)} u_{2,i}^{(2)} = 0.4$. Therefore, fluctuations are expected to be amplified in the second layer. Indeed, Fig. 5 shows the first escape time in both layers, and the second layer leaves the initial basin of attraction many orders of magnitudes faster than the first one for low values of η_0 .




FIG. 5. First escape time T_{esc} as a function of the noise amplitude in the first layer η_0 with $d = 1$. This system is composed of two different networks of size $n = 80$ in each layer, which have been generated using Watts–Strogatz procedure starting from coupling to first and second nearest neighbors and rewiring probabilities $p = 0.01$ (first layer), $p = 0.04$ (second layer). Each cross gives the median over 40 realizations. The solid lines show the median first escape time for the first (blue) and second (red) layers. Shaded areas show the 0.25- and 0.75-quantiles.




FIG. 6. First escape time T_{esc} as a function of the noise amplitude in the first layer η_0 with $d = \left(2 / \sum_{\alpha} \lambda_{\alpha}^{(1)-1}\right)^{1/2}$. This system is composed of two different networks of size $n = 80$ in each layer, which have been generated using the Watts–Strogatz procedure starting from coupling to first and second nearest neighbors (same networks as Fig. 5). Each cross gives the median over 40 realizations. The solid lines show the median first escape time for the first (blue) and second (red) layer. Shaded areas show the 0.25- and 0.75-quantiles.

2. Rescaled noise

Following the same steps as in Sec. III A 2 to emphasize the effect of the shape of the noise, I rescale the noise such that Eq. (10) is satisfied. This allows us to have injected noises of similar variance on average in each layer. Remarkably, Fig. 6 shows that the first escape time in the second layer is still shorter than in the first layer, despite the rescaling of the noise for $\eta_0 < 2.6$. The shape that the noise acquires when passing through the first layer seems to be more efficient in driving the second layer outside its initial basin of attraction, as in the previous case of two times the same network.

IV. CONCLUSION

Noisy layered systems can exhibit amplified fluctuation patterns depending on their connectivity. Here, I showed that noise originally injected in one layer may induce faster basin escape in connected layers. This is both due to the amplification of the noise amplitude and the system-specific correlations that the noise acquires while going through the first layer. Indeed, from Eq. (6), one sees that the noise in the second layer is correlated in both space and time with clear dependence on the network structure. For networks with low algebraic connectivity, I numerically showed that the first escape time is shorter in the two cases where (i) fluctuations are amplified in the second layer and (ii) noise in the second layer is rescaled in order to have the same variance in both layers. While point (i) is rather intuitive, i.e., larger fluctuations lead to shorter first escape times, point (ii) is more involved. Indeed, this indicates that noise with spatial and temporal correlations given by Eq. (6) selects directions that enable faster exits from the initial basin of attraction.

Even though I consider Kuramoto oscillators, the results presented here may apply to other nonlinear coupling functions as long as the system has an equilibrium point. Further studies should consider time-correlated noise injected in the first layer and the effect of inertia.

ACKNOWLEDGMENTS

This work was supported by U.S. DOE/OE as part of the DOE Advanced Sensor and Data Analytics Program and by the Laboratory Directed Research and Development program of Los Alamos National Laboratory under Project Nos. 20220797PRD2 and 20220774ER.

AUTHOR DECLARATIONS

Conflict of Interest

The authors have no conflicts to disclose.

Author Contributions

Melvyn Tyloo: Conceptualization (lead); Data curation (lead); Investigation (lead); Methodology (lead); Visualization (lead); Writing – original draft (lead); Writing – review & editing (lead).

DATA AVAILABILITY

The data that support the findings of this study are available from the corresponding author upon reasonable request.

APPENDIX: CALCULATION DETAILS TO OBTAIN EQ. (5)

In order to calculate $\langle \delta x_i^2 \rangle$, one needs the solution to the first line of Eq. (4). The latter is obtained by expanding the δx_i 's over the eigenvectors of $\mathbb{L}^{(1)}$, i.e., $\delta x_i = \sum_{\alpha} c_{\alpha}^{(1)} u_{\alpha,i}^{(1)}$, which yields the differential equations,

$$\dot{c}_{\alpha}^{(1)} + \lambda_{\alpha}^{(1)} c_{\alpha}^{(1)} = \sum_i \eta_i u_{\alpha,i}^{(1)}, \quad \alpha = 1, \dots, n. \quad (\text{A1})$$

The solution of the latter equations is given by

$$c_{\alpha}^{(1)}(t) = e^{-\lambda_{\alpha}^{(1)} t} \int_0^t e^{\lambda_{\alpha}^{(1)} t'} \sum_i \eta_i u_{\alpha,i}^{(1)} dt', \quad (\text{A2})$$

where the initial condition is $c_{\alpha}^{(1)}(t=0) = 0 \forall \alpha$. Then, the long time limit of the variance in the first layer is given by

$$\langle \delta x_i^2 \rangle = \sum_{\alpha, \beta} \langle c_{\alpha}^{(1)} c_{\beta}^{(1)} \rangle u_{\alpha,i}^{(1)} u_{\beta,i}^{(1)} \quad (\text{A3})$$

$$= \sum_{\alpha} e^{-2\lambda_{\alpha}^{(1)} t} \int_0^t e^{2\lambda_{\alpha}^{(1)} t'} \eta_0^2 u_{\alpha,i}^{(1)2} dt', \quad (\text{A4})$$

where in the last equality, I used $\langle \eta_i(t) \eta_j(t') \rangle = \delta_{ij} \eta_0^2 \delta(t-t')$ and the orthogonality between the eigenvectors. Performing the integral and taking the limit of a long time gives the results of Eq. (5).

REFERENCES

¹M. Tyloo, "Layered complex networks as fluctuation amplifiers," *J. Phys. Complex* **3**, 03LT01 (2022).

²M. Pedersen, A. Zalesky, A. Omidvarnia, and G. D. Jackson, "Multilayer network switching rate predicts brain performance," *Proc. Natl. Acad. Sci. U.S.A.* **115**, 13376–13381 (2018).

³J. Machowski, J. W. Bialek, and J. R. Bumby, *Power System Dynamics*, 2nd ed. (Wiley, Chichester, 2008).

⁴A. Pikovsky, M. Rosenblum, and J. Kurths, *Synchronization: A Universal Concept in Nonlinear Sciences* (Cambridge University Press, 2003).

⁵D. A. Wiley, S. H. Strogatz, and M. Girvan, "The size of the sync basin," *Chaos* **16**, 015103 (2006).

⁶P. J. Menck, J. Heitzig, N. Marwan, and J. Kurths, "How basin stability complements the linear-stability paradigm," *Nat. Phys.* **9**, 89 (2013).

⁷I. Simonsen, L. Buzna, K. Peters, S. Bornholdt, and D. Helbing, "Transient dynamics increasing network vulnerability to cascading failures," *Phys. Rev. Lett.* **100**, 218701 (2008).

⁸L. DeVille, "Transitions amongst synchronous solutions in the stochastic Kuramoto model," *Nonlinearity* **25**, 1473–1494 (2012).

⁹B. Schäfer, M. Matthiae, X. Zhang, M. Rohden, M. Timme, and D. Witthaut, "Escape routes, weak links, and desynchronization in fluctuation-driven networks," *Phys. Rev. E* **95**, 060203(R) (2017).

¹⁰J. Hindes and I. B. Schwartz, "Rare slips in fluctuating synchronized oscillator networks," *Chaos* **28**, 071106 (2018).

¹¹M. Tyloo, R. Delabays, and P. Jacquod, "Noise-induced desynchronization and stochastic escape from equilibrium in complex networks," *Phys. Rev. E* **99**, 062213 (2019).

¹²M. Kurant and P. Thiran, "Layered complex networks," *Phys. Rev. Lett.* **96**, 138701 (2006).

¹³G. Bianconi, *Multilayer Networks: Structure and Function* (Oxford University Press, 2018).

¹⁴T. Njouougou, V. Camargo, P. Louodop, F. Fagundes Ferreira, P. K. Talla, and H. A. Cerdeira, "Dynamics of multilayer networks with amplification," *Chaos* **30**, 123136 (2020).

¹⁵Y. Kuramoto, "Self-entrainment of a population of coupled non-linear oscillators," in *International Symposium on Mathematical Problems in Theoretical Physics*, Lecture Notes in Physics Vol. 39, edited by H. Araki (Springer, Berlin, 1975).

¹⁶R. Delabays, M. Tyloo, and P. Jacquod, "The size of the sync basin revisited," *Chaos* **27**, 103109 (2017).

¹⁷Y. Zhang and S. H. Strogatz, "Basins with tentacles," *Phys. Rev. Lett.* **127**, 194101 (2021).

¹⁸D. J. Watts and S. H. Strogatz, "Collective dynamics of "small-world" networks," *Nature* **393**, 440–442 (1998).